

Auxiliary contact blocks for AF09 ... AF96 contactors and NF control relays



CA4-10



CAL4-11



CA4-22E



CAT4-11E

Description

The auxiliary contact blocks are used for the operation of auxiliary circuits and control circuits for standard industrial environments.

Types of auxiliary contact blocks for front mounting:

- CA4 1 or 4-pole block, with instantaneous N.O., N.C. contacts
- CC4 1-pole block, with N.O. leading contact or N.C. lagging contact
- CAT4 2-pole block, with instantaneous N.O. + N.C. contacts and A1 / A2 coil terminal connection on front face.

Select the 4-pole auxiliary contact blocks CA4-..E, CA4-..M, CA4-..U or CA4-..N type, according to the contactor or contactor relay type for compliance with the standard requirements (see "Terminal marking and positioning").

Types of auxiliary contact blocks for side mounting:

- CAL4 2-pole block, with instantaneous N.O. + N.C. contacts.

For clipping onto the right- and/or left-hand side of the contactors.

The auxiliary contact blocks are equipped with screw type connecting terminals delivered open, protected against accidental direct contact and bear the corresponding function marking.

Ordering details (1)

For contactors	Auxiliary contacts	Catalog number	Global reference code	Pkg qty	Weight (1 pce)
	   				kg

Front-mounted instantaneous auxiliary contact blocks

AF09 ... AF96 4-pole NF	1	0	–	–	CA4-10	1SBN010110R1010	1	0.014
	1	0	–	–	CA4-10-T	1SBN010110T1010	10	0.014
	0	1	–	–	CA4-01	1SBN010110R1001	1	0.014
	0	1	–	–	CA4-01-T	1SBN010110T1001	10	0.014
AF09 ... AF16...-30-10	2	2	–	–	CA4-22M	1SBN010140R1122	1	0.055
	3	1	–	–	CA4-31M	1SBN010140R1131	1	0.055
	1	3	–	–	CA4-13M	1SBN010140R1113	1	0.055
	0	4	–	–	CA4-04M	1SBN010140R1104	1	0.055
AF26 ... AF96...-30-00 AF09 ... AF38...-40-00 AF09 ... AF38...-22-00	2	2	–	–	CA4-22E	1SBN010140R1022	1	0.055
	3	1	–	–	CA4-31E	1SBN010140R1031	1	0.055
	4	0	–	–	CA4-40E	1SBN010140R1040	1	0.055
	0	4	–	–	CA4-04E	1SBN010140R1004	1	0.055
AF09 ... AF16...-30-01	2	2	–	–	CA4-22U	1SBN010140R1322	1	0.055
	3	1	–	–	CA4-31U	1SBN010140R1331	1	0.055
	4	0	–	–	CA4-40U	1SBN010140R1340	1	0.055
	2	2	–	–	CA4-22N	1SBN010140R1222	1	0.055
4-pole NF	3	1	–	–	CA4-31N	1SBN010140R1231	1	0.055
	4	0	–	–	CA4-40N	1SBN010140R1240	1	0.055
	1	3	–	–	CA4-13N	1SBN010140R1213	1	0.055
	0	4	–	–	CA4-04N	1SBN010140R1204	1	0.055
NF..40E								

Front-mounted auxiliary contact blocks with N.O. leading contact and N.C. lagging contact

AF09 ... AF96 4-pole NF	–	–	1	0	CC4-10	1SBN010111R1010	1	0.014
	–	–	0	1	CC4-01	1SBN010111R1001	1	0.014

Side-mounted instantaneous auxiliary contact blocks

AF09 ... AF96 NF	1	1	–	–	CAL4-11	1SBN010120R1011	1	0.040
	1	1	–	–	CAL4-11-T	1SBN010120T1011	10	0.040

Front-mounted instantaneous auxiliary contact and A1/A2 coil terminal blocks

AF09 ... AF16...-30-10	1	1	–	–	CAT4-11M	1SBN010151R1111	1	0.040
AF26 ... AF65...-30-00 AF09 ... AF38...-40-00 AF09 ... AF38...-22-00	1	1	–	–	CAT4-11E	1SBN010151R1011	1	0.040
AF09 ... AF16...-30-01	1	1	–	–	CAT4-11U	1SBN010151R1311	1	0.040

(1) For each contactor or contactor relay type, refer to "Accessory fitting details" table.

Note: CAT4 not suitable for AF.Z contactors with DC control voltage 12...20 V DC.